

PYLE
PyleUSA.com



PC0885

19" Rack Mount Power Conditioner
3000 Watt Power Conditioner with 18 Outlets

USER GUIDE

This unit was developed using the expertise of professional sound engineers and working musicians. You will find your new unit has superior performance and greater flexibility than any other power conditioner in its price range. **READ THIS MANUAL CAREFULLY TO GET THE MOST OUT OF YOUR NEW UNIT.**

Features

For advanced RF/EMI noise filtering and the quietest operation of your equipment..

- Triple Mode Varistor Surge And Spike Protection
- 4 Front and 14 Rear Outlets (With Room For 4 " Wall Warts")
- 25A Safety switch on Rear Panel with Circuit Breaker and Leakage Protector
- Rugged Single Rack Space Metal Housing For Maximum Reliability



CAUTION
RISK OF ELECTRIC SHOCK
DO NOT OPEN



ATTENTION: RISQUE DE CHOC ELECTRIQUE NE PAS OUVRIR

**CAUTION: TO REDUCE THE RISK OF ELECTRIC SHOCK
DO NOT REMOVE COVER (OR BACK).
NO USER SERVICEABLE PARTS INSIDE.
REFER TO SERVICING TO QUALIFIED SERVICE PERSONNEL.**



An equilateral triangle enclosing a lightening flash/arrowhead symbol is intended to alert the user to the presence of uninsulated “dangerous voltage” within the product’s enclosure which may be of sufficient magnitude to constitute a risk of electric shock.



An equilateral triangle enclosing an exclamation point is intended to alert the user to the presence of important operating and service instructions in the literature enclosed with this unit.



WARNING:

This products can expose you to a chemical or group of chemicals, which may include “**Nickel Carbonate**” which is known in the state of California to cause cancer, birth defects, or other reproductive harm. For more info, go to <https://www.p65warnings.ca.gov/>.

IMPORTANT SAFETY INSTRUCTIONS

WARNING! When using electric products, basic precautions should always be followed, including the following:

1. Read all the instruction before using the product.
2. **DO NOT** use this product near water (e.g. near a bathtub, washbowl, kitchen sink, in a wet basement, or near a swimming pool etc.).
3. This product should be used only with a cart or stand that will keep it level and stable and prevent wobbling.
4. This product, in combination with amplifiers, headphones or speakers, may be capable of producing sound levels that could cause permanent hearing loss. Do not operate for a long period of time at a high volume level or at a level that is uncomfortable. If you experience many hearing loss or ringing in the ears, you should consult an audiologist.
5. The product should be located so that its location or position does not interfere with its proper ventilation.
6. The product should be located away from heat sources such as radiators, heat vent, or other devices (including amplifiers) that produce heat.
7. The product should be connected to a power supply only of the type described in the operating instructions or as marked on the product.
8. The power supply cord should:
 - Be undamaged
 - Never share an outlet or extension cord with other devices so that the outlet's extension on cord's power rating is exceeded.
 - Be left plugged into the outlet when left unused for a long period of time.
9. Care should be taken so that objects do not fall into, and liquids are not spilled through, the enclosure's openings.
10. **The products should be serviced by qualified service personnel when:**
 - A.** The power supply cord or the plug has been damaged.
 - B.** Objects have fallen into, or liquid has been spilled onto the product.
 - C.** The product has been exposed to rain.
 - D.** The product does not appear to operate normally or exhibits a marked change in performance.
 - E.** The product has been dropped, or the enclosure damaged.
11. Do not attempt to service the product beyond what is described in the user-maintenance instructions. All other servicing should be referred to qualified service personnel.
12. Do not defeat the safety purpose of the grounding-type plug, which features a third grounding prong. If this provided plug does not fit into your outlet, consult an electrician for replacement of the obsolete outlet.

FRONT & BACK PANEL FEATURES:



1. **POWER SWITCH:** Outlet switch activates protection and filtration to all outlets. To turn the unit ON or OFF, press the upper or lower portion of this button.
2. **Voltage LED Digital Screen**
3. **Dual USB Charge (5V/2A):** Charge for Mobile-phone
4. **4 FRONT PANEL OUTLETS**
5. **14 REAR PANEL OUTLETS:** EMI/RFI Filtered, spike/surge protected and switched.
6. **SAFETY SWITCH:** 25Amp circuit breaker, leakage protector.
7. **POWER CORD:** Heavy duty 14-gauge power cord for connection to the AC Power Mains (115V/60Hz).

INSTALLATION AND OPERATION

1. The Power Conditioners are the perfect accessories for any rack mount system. Install in the top slot of a standard 19-inch rack, and the 4 Front and 14 switched AC outlets on the rear panel will provide full safety protection to all your rack equipment. These conditioners protect your delicate electronic equipment by combining a high voltage varistor surge and transient suppressor with an RFI/EMI interference filter. The filter helps prevent noise from fluorescent lights, motors, and similar sources of “**electronic pollution**” from contaminating the AC feed to your sensitive video, audio, vtr or computer circuits.
2. Plug Power Cord (7) into a standard grounded 120V outlet.
3. Plug sensitive electronic equipment into the 14 Rear Panel Outlets (5)
4. Turn Outlet Power Switch (1) to “ON” position. Lit LED indicates conditioned power to the connected equipment.

5. MAXIMUM LOAD:

The Power Conditioners 4 Front and 14 Rear Panel Outlets are rated at 25 amps total load (or 3000W at 120VAC). If this maximum load is exceeded, the Circuit Breaker will trip, cutting off power to all connected equipment in your rack. If this happens, reduce the load by unplugging one or more units from the power conditioner, and then press "R" button and turn on the Red switch again.



R Button: It will be always DOWN, when the circuit is fine. It will only be UP when the circuit is OFF. Press the "R" button before turning ON the RED switch.

T Button: Press it monthly to make sure the Safety switch is working good.

FEATURES:

- Triple Mode Varistor Surge And Spike Protection
- 14 Rear Outlets (With Room For 4 " Wall Warts") Controlled By A Front Panel Switch
- 4 Front Outlets
- 2 USB Front Outlets (5V x 2A)
- Digital Voltage Display Screen
- 25 Amp Safety switch with Circuit Breaker and Leakage Protector
- Rugged Single Rack Space Metal Housing For Maximum Reliability
- Eliminates Unwanted Radio Frequency Interference (RFI) and Electromagnetic Interference (EMI)
- Overload and Surge Protection
- 2U Rack Mountable
- Steel Front Panel and Chassis
- Push to Reset

WHAT'S IN THE BOX:

- 18-Outlet Rack Mount Power Conditioner

TECHNICAL SPECS:

- Power Supply: 120V/60Hz, UL Standard Socket
- Construction Material: Iron
- 6.56 Foot Power Cord
- Maximum Load: 3000 Watts
- Product Dimensions (L x W x H): 48X18.5X9 cm 19" x 7.28" x 3.54" -inches

PYLE

PyleUSA.com



VISIT US ONLINE:

Have a question?

Need service or repair?

Want to leave a comment?

PyleUSA.com/ContactUs

PYLE

Questions? Issues?

We are here to help!

Phone: (1) 718-535-1800

Email: support@pyleusa.com