

PRTPMX6BURC



PYLE
PyleUSA.com

Wireless Audio DJ Sound Receiver

USER MANUAL

Multi-Receiver Connection:

Connecting Additional Receivers / Speakers to the PMX6BU - DJ Sound FX Audio Mixer System...

1. Designate one receiver to act as the **'MAIN RECEIVER'** -- and place it to the side.
2. Press the **'POWER'** button on all additional receiver units you are attempting to connect (the **'EMIT'** indicator lights will blink).
3. While the **'EMIT'** indicator is blinking, press the **'5.8G/BT'** button (the **'EMIT'** indicator light will stop blinking and the **'RXD'** indicator light will remain solid).
4. While the **'RXD'** indicator light remains solid, press and hold the **'5.8G/BT'** button for ~ 5 seconds (or until the **'EMIT'** indicator blinks red).
5. While the **'EMIT'** indicators blink red on all additional receiver units, press the **'POWER'** button on the designated **'MAIN RECEIVER'** (the **'EMIT'** indicator will blink).
6. While the **'EMIT'** indicator blinks on the **'MAIN RECEIVER'**, press and hold the **'5.8G/BT'** button for ~ 5 seconds (or until the **'EMIT'** indicator blinks red).
7. Wait for the indicator lights on the additional receiver units to stop blinking -- this ensures they are successfully paired (however, the **'MAIN RECEIVER'** indicator lights will continue to blink).
8. While only the indicator light on the **'MAIN RECEIVER'** is blinking, it's time to connect via Bluetooth. Go to your device's Bluetooth network list and get connected (upon successful Bluetooth connection, the **'MAIN RECEIVER'** indicator light will remain lit).
9. Stream some sound! The **'MAIN RECEIVER'** will deliver the wireless audio to any paired additional receiver units. Ensure all receiver units are connected to a compatible speaker with the audio connection cables via the **'AUX OUTPUT'**.

Notes:

- **Pyle Model: PMX6BU - DJ Sound FX Audio Mixer, sold separately.**
- When pairing the system, ensure both the mixer and wireless receiver(s) are within range pairing sequence.
- Ensure you are using a compatible speaker system with Aux audio line-in mode is activated on the connected speaker.



VISIT US ONLINE:
Have a question?
Need service or repair?
Want to leave a comment?
PyleUSA.com/ContactUs

PYLE

